



AC-11/AC-15/AC-15EX/AC-16 Series

Non-Contact AC Voltage Detectors

The Non-contact AC Voltage Testers are easy to use — just touch the tip to a terminal strip, outlet, or supply cord. When the tip glows red and the unit beeps, you know there's voltage present. Electricians, maintenance, service, safety personnel, and homeowners can quickly test for energized circuits in the workplace or at home.

پتروفرهان گستر جنوب

DIGINDT.IR

FGJ-NDT.IR



Specifications												
		A C- 11	A C- 11 B	A C- 11 S	A C- 15	A C- 15 B	A C- 15 S	A C- 15 Ex	A C- 15 E xs	A C- 16	A C- 16 B	A C- 16 S
ACV Non-Contact Detection		*	*	*	*	*	*	*	*	*	*	*
Operating Range(50Hz/60Hz)	12V to 100V	*			*			*		*		
	24V to 100V		*			*					*	
	50V to 100V			*			*		*			*
	100V to 1000V	*	*		*	*		*		*	*	

	200 V to 1000 V			*			*		*		*
IP67 Water proof & 2m drop-proof		2m drop-proof		*	*	*	*	*	*	*	*
Motor Shaking			*			*		*			*
Ex ib IIB T4 (ATEX)							*	*			
Dual Voltage Sensitivity detector											
Red/Yellow/Green LED indicators											
Flashlight function											
Auto Power Off											
Beeper sounds											
System self test											
Switchable audible and silent mode											
Rugged, double molded case											
CATIV-1000V											
Size(HxWxD)	160 x 20 x 23		160mm x 23mm x 25mm			155mm x 20mm x 22mm					
Weight	60g		55g			48g					

 **+982165565901**

 **+982144584619**

 **+989034119385**

 **Tehran, Tehransar**