



EMC & LVD
EN: 61326
EN: 61010-1
EN: 61010-02-032
EN: 61010-02-033



Model 991



Model 204

991/200 Series Mini Digital Multimeters provide multifunction and lower price. Rugged pocket design is easy and safe to use with protective holster.

Safety Conformance

- EN61010-1 CATII 600V
- Includes protective holster
- 10A fused protection

Specifications

Function	Max Range	Basic Accuracy	991/200	992/201	993/202	202T	204	204T
Voltage DC	600V	±(0.8%±2d)	*	*	*	*	*	*
Voltage AC	600V	±(1.2%±10d)	*	*	*	*	*	*
Current DC	10A	±(1.2%±2d)	*	*	*	*	*	*
Current AC	10A	±(1.8%±7d)	*	*/-	*	*	*	*
Resistance	2000Ω	±(0.8%±2d)	*	*	20MΩ			20MΩ
	40MΩ	±(0.8%±2d)	*	*				
Temperature	760°C/1400°F	±(3.0%±3d)			*	*	*	*
Duty Cycle	0.1%-99.9%	±(1.2%±2d)		*	*	*	*	*
Frequency	9.999MHz	±(1.5%±4d)			*	*	*	*
Capacitance	200uF	±(2.5%±5d)			*	*		
	40mF	±(2.5%±5d)					*	*
Diode Check	Open voltage 2.8Vdc; Test current 1mA		*	*	*	*	*	*
Continuity	Threshold 30Ω		*	*	*	*	*	*
Bat. Test	9V(6mA); 1.5V(100mA)		*					

991 Series:

Size(HxWxD): 121.5mm x 60.6mm x 40mm
Weight: 150g

Accessories:

Test leads, Holster and 9V battery, clamshell.

200 Series:

Size(HxWxD): 146mm x 66.2mm x 41.5mm
Weight: 200g

Accessories:

Test leads, K-type temperature probe (201, 202, 202T, 204, 204T) and 9V battery, gift box.



Model 9932FC



EMC & LVD
EN: 61326
EN: 61010-1
EN: 61010-02-032
EN: 61010-02-033

Specifications

Function	Max Range	Min Resolution	Basic Accuracy
Voltage DC	1000V	0.1mV	±(1.2%±2d)
Voltage AC	750V	0.1mV	±(0.8%±3d)
Current DC	20A	0.1uA	±(1.5%±3d)
Current AC	20A	0.1uA	±(1.8%±5d)
Resistance	40MΩ	0.1Ω	±(1.0%±2d)
Capacitance	100uF	10pF	±(3.5%±5d)
Frequency	9.999MHz	0.001Hz	±(1.2%±3d)
Duty Cycle	99.9%	0.1%	±(1.2%±2d)
Temperature	1000°C/1832°F	0.1°C/°F	±(3%±2°C/°F)
Diode Check	1.5VDC test 0.3mA current		
Continuity Check	Threshold 30Ω, continuity beeper 2.7kHz		

Size(HxWxD): 197mm x 88.4mm x 41.2mm
Weight: 635g

Accessories :

Rubber holster, Test leads, K-type temperature probe, 9V battery, RS-232 PC cable and Software diskette, Gift box with carrying case.

