

Watt, Leakage current, ACV, DCV, DCV, ohms, Beeper

WATT/Leakage METER

Model : DW-6160

ISO-9001, CE, IEC1010

FGJ-NDT.IR
DIGINDT.IR



+982165565901

+982144584619

+989034119385

پتروفرهان گستر جنوب

Lutron

LUTRON ELECTRONIC



The Art of Measurement

**FEATURES**

- * Professional WATT meter with Leakage current tester, digital display, battery operated.
- * LSI - circuit provides high reliability and durability.
- * Measurement :
WATT (AC) : 2500 W x 0.1 W/1 W.
Leakage current (AC mA) : 20.00 mA x 0.01 mA.
ACV : 600.0 V x 0.01 V/0.1 V.
ACA : 10.00 A x 0.001 A/0.01 A.
DCV : 600.0 V x 0.01 V/0.1 V.
ohm : 2 K ohm x 0.001 K ohm, 20 K ohm x 0.01 K ohm
- * Low Watt measurement, 1.0 to 999.9 Watt x 0.1 Watt.
- * True Power and wide range, 0 to 2500 Watt.
- * True RMS ACV, ACA measurement.
- * Leakage current (AC mA) detection.
- * Auto range.
- * Continuity beeper.
- * Large LCD, dual value display with backlight.
- * Memory Record (Max., Min.).
- * Data Hold.
- * RS232/USB computer interface.
- * Power : DC 1.5V (UM-3, AA) x 8 PCs or DC 9V adapter in.

GENERAL SPECIFICATIONS

Circuit	Custom one-chip of microprocessor LSI circuit.
Display	LCD display, max. reading 5999. Digit size : 74x47 mm. Dual value display with backlight
Measurement	ACV 0.1 to 600.0 V DCV 0.1 to 600.0V Ω 0.001 k Ω to 20.00 k Ω WATT 0.1 W to 2500 W Leakage current 0.01mA to 20.00 mA ACA 0.001A to 10.00 A
Over input	---- " mark indication .
Polarity	** reverse polarity.
Zero Adjustment	Automatic adjustment.
Sampling Time	Approx. 1.5 second.
Data Hold	Freeze the display reading.
Memory Recall	Maximum & Minimum value.
Data Output	RS 232/USB PC computer interface. * Connect the optional RS232 cable UPCB-02 will get the RS232 plug. * Connect the optional USB cable USB-01 will get the USB plug.
Operating Temperature	0 to 50 °C.
Operating Humidity	Less than 80% R.H.
Power Supply	* Alkaline or heavy duty DC 1.5 V battery (UM3, AA) x 8 PCs, or equivalent. * DC 9V adapter input. (AC/DC power adapter is optional).
Power Consumption	Approx. DC 33 mA.
Weight	822 g/1.82 LB.
Dimension	224 x 125 x 65 mm (8.8 x 4.8 x 2.5 inch)
Accessories Included	* Instruction manual..... 1 PC * Test lead (Red and Black)..... 1 pair
Optional Accessories	* AC to DC 9V adapter. * USB cable, USB-01. * RS232 cable, UPCB-02.

Optional Accessories

- * Data Acquisition software, SW-U801-WIN.
- * Hard carrying case, CA-08

ELECTRICAL SPECIFICATIONS (23± 5 °C)**AC / DC VOLTAGE**

Range	Resolution	Accuracy
0.01 V to 99.99 V	0.01 V	ACV : ± (1 % + 5d) DCV : ± (0.8 % + 5d)
100.0 V to 600 V	0.1 V	ACV : ± (1 % + 5d) DCV : ± (0.8 % + 5d)

- * Measuring Signals come from the front panel terminals.
- * Auto range.
- * Max. input voltage : AC 600 V, DC 600 V.
- * ACV accuracy is test under input signal is sine wave, 50/60 Hz
- * ACV frequency response is from 40 to 400 Hz.
- * ACV is true rms measurement..

OHMS (Resistance)

Range	Resolution	Accuracy
2 K Ω	1 Ω	± (1 % + 1d)
20 K Ω	10 Ω	± (1 % + 1d)

- * Auto range.
- * Continuity beeper : < 4 Ω .
- * Overload Rating : AC / DC 600V at 20 second Max

WATT (true power)

Range	Resolution	Accuracy
1000 W	0.1 W	± (1.5 % + 5d)
1001 to 2500 W	1 W	± (1.5 % + 5d)

- * 0.1 W resolution : Input voltage < 200 AVC or Input current < 2 ACA.
- Beyond above input, the resolution will still be 1 W.
- * Measuring Signals come from the top power plug input..
- * Accuracy is test under input signal is sine wave, 50/60 Hz
- * ACV, ACA frequency response is from 40 to 400 Hz.
- * Max. input voltage : AC voltage 250 V, AC current : 10 A.

Leakage (AC mA)

Range	Resolution	Accuracy
0 to 20 mA	0.01 mA	± (1 % + 5d)

- * The leakage current that sense between the " Hot line " and the " Earth " of the measuring installation that connect to the output " Power plug "

☎ +982165565901

V, A (true rms)

☎ +982144584619

☎ +989034119385

Range	Resolution	Accuracy
ACV 250 V	0.01 V/0.1 V	± (1 % + 5d)
ACA 10 A	0.001 A/0.01A	± (1 % + 3d)

- * ACV, 0.01 V resolution is valid from 0.01 V to 99.99 V.
- ACV, 0.1 V resolution is valid from > 100.0 V.
- * ACA, 0.001 A resolution is valid from 0.001 A to 1.999 A.
- ACA, 0.01 A resolution is valid from > 2 A.
- * Measuring signals come from the top power plug input (power source).
- * Auto range.
- * ACV, ACA accuracy is test under input signal is sine wave, 50/60 Hz
- * ACV, ACA frequency response is from 40 to 400 Hz.
- * ACV, ACA is true rms measurement..
- * Max. input voltage : AC voltage 250 V, AC current : 10 A.