



Pocket Digital Multimeter

Model: DT-10/12/16/16A



4000 counts, 8 functions including DCV, ACV, DCA, ACA, Resistance, Continuity, Diode test with Data Hold, Low impedance and non-contact ACV detection.

Large high contrast 4000 counts LCD display with Analog barograph

Auto Power off

Relative, and Data Hold

Built-in storage compartment for integrated test leads

Over-range and low battery indication

Features:

Size (H x W x D): 126mm x 59mm x 32mm

Weight: 124g

Specifications:

Specifications	DT-10	
Function	Max. Range	Accuracy
Voltage DC	600V	$\pm(1.3\% \pm 2d)$
Voltage AC	600V	$\pm(2.3\% \pm 5d)$
Current DC	200mA	$\pm(1.5\% \pm 2d)$
	4000 μ A/6000 μ A	$\pm(2.5\% \pm 5d)$
Current AC	200mA	$\pm(2.5\% \pm 5d)$
	4000 μ A/6000 μ A	$\pm(2.5\% \pm 5d)$
Resistance	40M Ω	$\pm(2.0\% \pm 2d)$
Continuity	Audible threshold < 50 Ω	
Diode Test	Test Current 0.6mA	

Pocket Digital Multimeter

Model: DT-10/12/16/16A

Accessories:

Test leads, Wallet style case and one 1.5V L44 button battery.

Application:



Pocket Digital Multimeter

- 4000 counts, 8 functions including DCV, ACV, DCA, ACA, Resistance, Continuity, Diode test with Data Hold, Low impedance and non-contact
- ACV detection.
- Large high contrast 4000 counts LCD display with Analog bargraph
- Auto Power off
- Relative, and Data Hold
- Built-in storage compartment for integrated test leads
- Over-range and low battery indication



Built-in Non-Contact Voltage Detector automatically detects a live wire when the red LED is lit



Oversized high contrast 4000/6000 counts LCD Display



Rubber Protection

+982165565901

+982144584619

+989034119385

بنروفرهان گستر جنوب

FGJ-NDT .IR

DIGINDT .IR