



RPM TRANSMITTER

Model : TR-RPM1A4

ISO-9001, CE, IEC1010



PX-01 (Optional)



LUTRON ELECTRONIC

The Art of Measurement

+982165565901

+982144584619

+989034119385

پتروفرهان گستر جنوب

FGJ-NDT.IR

DIGINDT.IR



RPM

TRANSMITTER

Model : TR-RPM1A4

Measure Range	<i>Range 1 :</i> 100-2,000RPM	<i>Range 2 :</i> 1,000 RPM - 20,000 RPM
Output	4 - 20 mA	
	<i>Range 1 :</i> 100 RPM = 4.8 mA 1,000 RPM = 12 mA 2,000 RPM = 20 mA	<i>Range 2 :</i> 1,000 RPM = 4.8 mA 10,000 RPM = 12 mA 20,000 RPM = 20 mA
External Adjustment	ZERO VR SPAN VR	
Power Supply	90 - 260 ACV 50 Hz/60 Hz	
Operation Temperature	0 - 50 °C 32 - 122 °F	
Operation Humidity	Less than 80 %RH	
Accessory Included	RPM sensor is optional.	
Optional Accessories	Proximity sensor: PX-01 Photo sensor: PI-06	
Mounting	Din rail or Wall	
Case	ABS plastic	
Others	*3 wires connection *Exciting voltage DC 12 V	

* Appearance and specifications listed in this brochure are subject to change without notice.

+982165565901

+982144584619

+989034119385

پتروفرهان گستر جنوب

FGJ-NDT.IR

DIGINDT.IR